

CAVITY NOTCH FILTER

PART NO. : WVR-1880B-56.2M01

◆ APPLICATION

> 1880MHz Band System

◆ FEATURE

> High Reliability
> **RoHS Compliant**

◆ ELECTRICAL SPECIFICATION

ITEM	SPEC
Reject Frequency Range	1852.6MHz ~ 1907.4MHz
Rejection	40dB Min @ 1852.6MHz ~ 1907.4MHz
3dB BW	3dB BW = C.F. $\pm$ 31MHz
Insertion Loss	2.0dB Max @ DC ~ 1835MHz, 1925MHz ~ 3000MHz
VSWR	1.5:1 Max @ DC ~ 1835MHz, 1925MHz ~ 3000MHz
In/Out Impedance	50 Ohms Nominal

◆ ENVIRONMENTAL SPECIFICATIONS

ITEM	SPECIFICATION
Operating Temperature Range	-30°C to +70°C

◆ MECHANICAL SPECIFICATIONS

ITEM	SPECIFICATION
Dimension	176.0 x 68.0 x 49.0 Max (Unit:mm)
Mounting Points	See Outline Drawing
RF Connector	All Ports : N Female Connector
Connector Position	See Outline Drawing
Finish	Black color epoxy coating

CAVITY NOTCH FILTER

◆ OUTLINE DRWAING

